



The set is designed to provide sound for processions, pilgrimages, etc. It includes a radio transmitting and receiving set, a wireless microphone and an MP3 player with a remote control. It is powered by an internal 12V gel battery. It has a built-in battery status signaling system. It has installed sockets for connecting: a microphone, additional loudspeakers such as megaphones, a charging adapter (power adapter included). It has volume control for remote and wired microphones and transmitter activation signaling. It is equipped with an adjustable symmetrical output from the wireless microphone receiver (one or two wireless microphones), used to use the ZP4-A set as a receiver from these wireless microphones for a stationary sound system.

Technical data	ZP4 - A	Megaphone	Stand
Rated power of the set [W]	20	2 x 30	-
Working frequency [MHz]	673.300 - 677.700 674.200 - 688.900 823.700 - 825.300 863.900 - 864.900	-	-
Powering the microphone	9V Battery		
Mic. Range wireless [m]	60	-	-
MP3 Player	yes		
MP3 player remote control	yes		
Supply voltage (internal battery) [V]	12V	-	-
System efficiency (1W / m) [dB]	92	108	-
System efficiency (max.) [DB]	105	121	
Band [Hz]	150-15 000	200-10 000	-
Audibility range [m]	50	150	-
Number of speakers	4	2	-
Height [cm]	52	35	135
Continuous operation time of the battery in full cycle after charging [hours]	3	3	-
Weight [kg]	3,9	3,1	2,3